



Coude 90° Femelle tournant - Femelle tournant



Coude 90° Femelle tournant JIC X Femelle tournant JIC



E90 FSJIC X FSJIC

PT535	JIC (E)	JIC (F)	L1	L2	d1	d2	H1	H2	SP	
1SE99410	7/16-20f	7/16-20f	16,7	16,7	4,4	4,4	15	15	11	
1SE99420	1/2-20f	1/2-20f	17,4	17,4	6	6	17	17	13	
1SE99430	9/16-18f	9/16-18f	22,3	22,3	7,5	7,5	19	19	14	
1SE99440	3/4-16f	3/4-16f	24,4	24,4	9,9	9,9	19	22	22	
1SE99450	7/8-14f	7/8-14f	28,4	28,4	12,3	12,3	27	27	22	
1SE99460	1"1/16-12f	1"1/16-12f	30,1	30,1	15,5	15,5	32	32	27	
1SE99470	1"5/16-12f	1"5/16-12f	30,5	30,5	21,2	21,2	41	41	30	

Coude 90° Femelle tournant BSP X Femelle tournant BSP



E90 FSBSP X FSBSP

PT565	BSP (E)	BSP (F)	L1	L2	d1	d2	H1	H2	SP	
1SE99700	G1/8-28f	G1/8-28f	20	20	3,5	3,5	14	14	11	
1SE99710	G1/4-19f	G1/4-19f	26	26	4,7	4,7	19	19	14	
1SE99720	G3/8-19f	G3/8-19f	30	30	7,9	7,9	22	22	19	
1SE99730	G1/2-14f	G1/2-14f	35	35	11,1	11,1	27	27	22	
1SE99740	G5/8-14f	G5/8-14f	38	38	14,3	14,3	30	30	24	
1SE99750	G3/4-14f	G3/4-14f	42	42	16,7	16,7	32	32	27	
1SE99760	G1"-11f	G1"-11f	44	44	22,2	22,2	41	41	33	
1SE99770	G1"1/4-11f	G1"1/4-11f	49	49	28,6	28,6	50	50	41	
1SE99780	G1"1/2-11f	G1"1/2-11f	61	61	33,3	33,3	55	55	48	
1SE99790	G2"-11f	G2"-11f	68	68	46	46	70	70	65	